

Programmable current limiting using a shunt resistor

TECHNICAL FIELD OF THE INVENTION

[001] This invention relates to current limiting and more particularly to programmable current limiting using a shunt resistor and a field-effect transistor, particularly in current limiting for a hot swap board application.

BACKGROUND OF THE INVENTION

[002] When a short circuit or current surge occurs on the load of a powered switch, or a switch is powered into a short circuit or heavy load, there occurs an excessive current through the switch. This current can destroy the switch by exceeding the safe-operating area of the switch, and damage the input power supply or cause a voltage transient on the input power supply network which can result in the malfunction of other circuitry due to the undervoltage condition. This problem is often evident when inserting or removing a circuit board under operating conditions ("hot swapping") into a powered backplane. Current limiting circuits are used to control the initial current and protect against voltage transients when hot swapping.

[003] Figure 1 shows a circuit diagram for a current limiting circuit used to allow safe hot swapping of a circuit board **10** according to a prior art design. The

circuit receives a voltage source V_s **12** and a voltage reference (GND) **14** from a connector **16** when connected to a back plane connector (not shown). A sense resistor R_s **18** is placed in series with a switch **20** between the input voltage source and the board load. The switch connects the voltage source to the board circuits which are indicated by the load capacitor C_L **22**. A control circuit **24** connects to the gate and controls the switch **20**. Inputs to the control circuit are from connections on either side of R_s . On the input voltage side of R_s a shunt resistor R_{SH} **26** is used in the connection to the control circuit **24**. The control circuit compares the voltage drop on R_s and the voltage drop on the shunt resistor **26** to control the input current through the switch **20**. The connections to the control circuit are shown with 45 degree connections to indicate Kelvin sense connections, which include a power wire and a sense wire to more accurately read the small voltage differences.

[004] Figure 2 shows a circuit diagram for a current limiting circuit according to another prior art design. Similar to the previous circuit, the switch connects the voltage source to the board circuits which are indicated by the load capacitor C_L **22**. A control circuit **24** connects to the gate and controls the switch **20**. In this circuit, inputs to the control circuit are from connections on either side of the switch. The control circuit monitors the voltage drop across the switch **20** to control the input current through the switch. In this prior art circuit, the control circuit merely checked for a threshold voltage drop and shut down the circuit for an emergency overload condition.

SUMMARY OF THE INVENTION

[005] The present invention overcomes some problems and provides advantages over the described prior art current limiting circuits. In the present invention the voltage drop across the conducting switch is used to regulate the conduction current. In an embodiment, the circuit uses a temperature dependent current source, a shunt resistor to set a voltage threshold, and an amplifier to guarantee the voltage drop across the switch does not exceed the voltage across the shunt resistor

[006] In an embodiment of the present invention, overcurrent protection is provided using a shunt resistor and the voltage drop across the switch to program a user-defined current limiting level. This protects the switch and the input power supply, as well as the load. The shunt resistor is connected to the input or output of the switch, and a temperature dependent current source, so that a voltage drop is generated across the shunt resistor. The voltage across the shunt resistor and the voltage drop across the switch are fed to an amplifier that controls the gate voltage of the switch. When the voltage drop across the switch exceeds the voltage drop across the shunt resistor, an amplifier will regulate the switch so that a voltage drop across the switch is equal to the voltage drop across the shunt resistor. In this way, a constant current through the switch can be achieved. A constant ratio between the current limiting level to the shunt resistor value can be achieved with this method, so the current limiting level is programmable by selecting the resistor value.

[007] The current source that sets the voltage drop across the shunt resistor is preferably a linear temperature dependent source, such as a PTAT (Proportional To Absolute Temperature) source, and can be adjusted by a resistor if so desired. The temperature dependency of the current source (presumably linear) which drives the shunt resistor largely compensates for variation of switch RDS(on) versus temperature, as neither the external power field-effect transistor (FET) switch nor the control chip dissipate large amounts of heat in normal operation.

[008] An advantage of an embodiment of the present invention is no sense resistor or other sense element is needed in the power conduction path. The sense element of the prior art adds an undesirable extra voltage drop in the power conduction path and an appreciable addition to the board's cost.

[009] Another advantage of an embodiment of the present invention is the current limiting level is programmable by one resistor external to the control circuit.

[010] Another advantage of an embodiment of the present invention is the circuit is largely compensated for variations in ambient temperature.

BRIEF DESCRIPTION OF THE DRAWINGS

[011] FIGURE 1 illustrates a circuit diagram according to the prior art.

[012] FIGURE 2 illustrates a circuit diagram according to the prior art.

[013] FIGURE 3a and 3b illustrates circuit diagrams according to an embodiment of the present invention.

[014] FIGURE 4 illustrates a circuit diagram according to an embodiment of the present invention.

[015] FIGURE 5 illustrates a circuit diagram of a control circuit according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[016] Figure 3a shows a circuit diagram for a current limiting circuit used to allow safe hot swapping of a circuit board **100** according to the present invention. The circuit receives a voltage source V_s **102** and a voltage reference (GND) **104** from a connector **106** when connected to a back plane connector (not shown). A switch **108** is connected between the input voltage source and the board load. The switch connects the voltage source to the board circuits which are indicated by the load capacitor C_L **110**. A control circuit **112** connects to the gate and controls the switch **108**. Inputs to the control circuit are from connections on either side of the switch. On the input voltage side of the switch, a shunt resistor **114** is used in the connection to the control circuit **112**.

[017] The control circuit compares the voltage drop across the switch and the voltage drop on the shunt resistor **114** to control the input current through the switch **108**. The current is held to a maximum current to charge the load capacitor on powerup or during an overload condition. In embodiments of the present invention, the $R_{DS(on)}$ will increase with increased current due to device self-heating. This will cause the current to fold back during an overcurrent condition.

[018] **FIGURE 4** illustrates a circuit diagram according to another embodiment of the present invention. This embodiment is substantially similar to the above embodiment, but includes further detail for the control circuit **112**. The circuit has the same voltage source V_s **102**, voltage reference (GND) **104**, and switch **108** connections as described for the embodiment in Figure 3. The control circuit **112** connects to the gate and controls the switch **108**. Inputs to the control circuit are from connections on either side of the switch. On the input voltage side of the switch, a shunt resistor **114** is used in the connection to the control circuit **112**. The shunt resistor is selected to set the threshold for the current limit for the switch **108**.

[019] In the preferred embodiment illustrated in Figure 4, the connections to the control circuit from either side of the switch are connected to an amplifier **116**. The connection from the shunt resistor is connected to the minus terminal, and the connection from the load side of the switch is connected to the plus terminal. The amplifier in the control circuit compares the voltage drop across the switch and the voltage drop across the shunt resistor **114** to control the input current through the switch **108** with the output of the amplifier connected to the gate of switch **108**. The switch **108** is preferably a field-effect transistor, where an N-type device is illustrated.

[020] Again referring to Figure 4, a current source **118** is preferably connected as shown from the minus input of the amplifier and the shunt resistor. The current source is used to bias the voltage on the shunt resistor. The current

source that sets the voltage drop across the shunt resistor is preferably a linear temperature dependent source, such as a PTAT (Proportional To Absolute Temperature) source, and can be adjusted by a resistor **120** if so desired. The temperature dependency of the current source (presumably linear) which drives the shunt resistor largely compensates for variation of RDS(on) versus temperature, as neither the external power FET nor the control chip dissipate large amounts of heat in normal operation.

Other Embodiments

[021] Although the present invention has been described in detail, it should be understood that various changes, substitutions, and alterations could be made hereto without departing from the spirit and scope of the invention as defined by the appended claims. For example, Figure **5** illustrates a circuit diagram according to another embodiment of the present invention. This embodiment is very similar to the above embodiment, except that the switch element **20** has been placed in the low side of the power source **14**.

[022] In another embodiment, a P-type device may be substituted for the N-type device providing that the polarities of the inputs of amplifier **116** are reversed.

[023] In another embodiment, the shunt resistor **114** may be placed in the control circuit connection to the output side of the switch rather than the supply side of the switch as shown in Figure **3b**. This embodiment would require the polarity of the current source **118** be reversed to push current into the shunt resistor rather than draw a current out. In this embodiment, similar to the previous embodiments, the voltage across the shunt resistor sets the voltage drop allowed across the switch before the amplifier activates.

[024] In another embodiment, the adjustment resistor **120** can be located outside the IC for the control circuit so that the user may select the bias current of the shunt resistor.